

Component Checks

High beam headlamp switch

Pin occupation, component side:

- NOTE: The value measured in the continuity test of the high beam switch should be less than 50 Ohm.

Circuit to test	Connect a digital multimeter with the following connections	Set the switch to the following position	Switch is OK when the following test readings are seen
Headlamp flasher	1 and 3	Off	Open circuit
		On	Closed circuit
High beam	1 and 6	Off	Open circuit
		On	Closed circuit
Left-hand turn signal	1 and 5	Neutral position	Open circuit
		On	Closed circuit
Right-hand turn signal	1 and 4	Neutral position	Open circuit
		On	Closed circuit